



Power generator

FH 3001 R

Nr art. 28152

Characteristic

- Voltage stabilization $\pm 1\%$
- Low level of THD $\leq 6\%$
- Shortcut starting current 300 %
- Alternator insulation class H
- Alternator protection IP IP 23

Technical parameters

Frequency	50 Hz
Voltage	230 V
Maximum power	2,7 kW
Nominal power	2,5 kW
Prime current	10,9 A
Engine	Honda
Model	GX 200
Capacity	196 cm ³
Cooling	Air
Cylinder	1
Stroke	4
Oil volume	0,6 L
Starting system	Manual
Fuel	Petrol
Fuel tank	3,1 L
Consumption (load 75%)	1,4 L / h
Noise level Lwa	96 dB(A)
Weight	38 kg
Length	580 mm
Width	395 mm
Height	405 mm

Standard equipment

- AVR
- 2 sockets 230 V 16 A
- Overload protection
- Oil level sensor

Optional and service equipment

- Exhaust hose Nr art. 15876
- Exhaust adapter Nr art. 10117
- Hourmeter Nr art. 23300
- Service kit
(air filter, spark plug, engine oil) Nr art. 16581

Norms and Directives

- **2000/14/WE**
Noise Directive 2005/88/WE
- **2006/42/WE**
Machinery Directive
- **2014/35/WE**
Low Voltage Directive
- **2014/30/WE**
EC Directive